

LAKSHMI “G-LITE” FOR NIGHT PATROLLER

INTRODUCTION: It can be used by hand cranking anytime anywhere. It can be used where electricity is not available. Portable, High Brightness, Long Lighting Range, Long Life – 5 years, maintenance Free, Water proof, Dust Proof, Safe & Reliable, Easy to use, Environment friendly are some of the special features.

TECHNICAL PARAMETER

- (1) Brightness 30000 Mcd
- (2) Lighting time after 10 minute cranking 40 minutes
- (3) Lighting time by external battery 40 hours
- (4) LED Life 50000 hours
- (5) Max Luminous 4Lm
- (6) Lighting distance beam goes beyond 60 meters
- (7) Weight 311.5 gm
- (8) Length 173mm*width69mm*height 56.5mm

SPECIAL FEATURE: There is no need of bulb and battery replacement. It has provision to charge the Mobile phone in emergency. Flasher mode is also provided.

USAGE:

- 1. Lighting:** Hold the unit by one hand and crank the handle with another hand at the speed of 2.5-3 circles per second for about 1 minute while the indicator at the side of DC port is on, press the button to use.
- 2. Charge a Mobile phone:** Open DC cap, connect the end with “DC” mark of cable with the DC port of this product and another end to the mobile phone or a suitable plug, crank it at the speed of 2.5-3 circles as per second to charge, the indicator will work during the charge.
- 3. Connect the product with external AC power to charge the unit:** Insert the plug of out- source adapter into the socket of DC port, the indicator is on to show on-charging.



(Right reserve for modification or alteration without notice for betterment of the product)

ISO 9001 : 2008

JAS-ANZ

C

M4579101N

(An ISO certified & RDSO approved Company)

LAKSHMI INDUSTRIAL CORPORATION

48-52, BEHIND OLD TEHSIL, MEERUT CITY- 250002 (U.P)
Admin Office: - Plot no.-10-11, Khasra no.-467, Mohkampur Industrial Area,
Phase-II, Delhi Road, Meerut City-250103(U.P.)
PH.NO: 0121-2401482 / 2950515

E-mail: railwaymachines@gmail.com

www.lakshmirailwaymachines.com